

Product Information



Xport™ Lubricant Application

Xport™ Single Point Lubricator Discharge Rates

Alternatively, determine the setting based on the stipulated discharge quantity.

Xport Flex & Star Vario

60–65 cc lubricant											
Setting/months	1	2	3	4	5	6	7	8	9...	...12	
Lubricant/day [cc]	2.0	1.0	0.7	0.5	0.4	0.3	0.3	0.3	0.2	0.2	
Lubricant/100 h [cc]	8.3	4.2	2.8	2.1	1.7	1.4	1.2	1.0	0.9	0.7	
Lubricant/week [cc]	14.0	7.0	4.7	3.5	2.8	2.3	2.0	1.8	1.6	1.6	
Strokes with grease gun/day	1–2	<1	0.5	-	-	0.25	-	-	-	0.13	
Strokes with grease gun/100 h	5–7	3	2	1.5	<1.5	1	<1	<1	<1	0.5	
Strokes with grease gun/week	9–11	5	3	2–3	2	1–2	<1.5	<1.5	1	<1	

CONVERSION

1 stroke grease gun = approx. 1.5 cc = 1.2 g lubricant

Xport Classic & Futura

120 cc lubricant					
Activator/ months at 20°C (68°F)	1	3	6	12	
Lubricant/day [cc]	4.0	1.3	0.7	0.3	
Lubricant/week [cc]	28.0	9.3	4.7	2.3	
Strokes with grease gun/day	2–3	1	0.5	0.25	
Strokes with grease gun/week	16–20	5–7	3–4	1–2	

TIP

Make note of activation and exchange date on label.



Xport Flex, Nova & Star Vario

120–125 cc lubricant											
Setting/months		1	2	3	4	5	6	7	8	9...	...12
Lubricant/day [cc]		4.2	2.1	1.4	1.0	0.8	0.7	0.6	0.5	0.5	0.4
Lubricant/100 h [cc]		17.4	8.7	5.8	4.3	3.5	2.9	2.5	2.2	1.9	1.6
Lubricant/week [cc]		29.2	14.6	9.7	7.3	5.8	4.9	4.2	3.6	3.2	2.6
Strokes with grease gun/day		3	1–2	1	<1	<1	0.5	-	-	-	0.25
Strokes with grease gun/100 h		11–13	5–7	4	3	2–3	2	<2	1.5	<1.5	1
Strokes with grease gun/week		18–22	9–11	6–7	5	4	3–4	3	2–3	2	1–2

CONVERSION
1 stroke grease gun = approx. 1.5 cc = 1.2 g lubricant

Xport Star Vario

250 cc lubricant											
Setting/months		1	2	3	4	5	6	7	8	9...	...12
Lubricant/day [cc]		8.3	4.2	2.8	2.1	1.7	1.4	1.2	1.0	0.9	0.7
Lubricant/100 h [cc]		34.7	17.4	11.6	8.7	6.9	5.8	5.0	4.3	3.9	3.1
Lubricant/week [cc]		58.3	29.2	19.4	14.6	11.7	9.7	8.3	7.3	6.5	5.2
Strokes with grease gun/day		5–6	3–4	2	1.5	<1.5	1	<1	<1	<1	0.5
Strokes with grease gun/100 h		22–24	9–13	7–9	5–7	4–6	3–5	2–4	1–3	2	1–2
Strokes with grease gun/week		36–40	18–21	12–14	9–11	7–9	6–7	5–6	5	4–5	3–4

TIP
Make note of activation and exchange date on label.